

PRE9220

Remote trigger delay timer



Cleverly simple
control of energy.



Key features

- Suitable for a variety of environments, particularly 'wet' areas – such as bathrooms, shower rooms, WCs etc.
- Switches loads up to 3kW heaters (16A resistive, 10A incandescent, 6A fluorescent, 3A low energy lighting)
- 230V AC at 50Hz
- Live, Neutral, Live output, 230VAC Live trigger
- Timing 0-2 hours selectable.
- Fits 25mm flush box.
- 4mm² terminal capacity
- 5-year warranty

The PRE9220 is a remote activated timer. This multi range timer can be used for a number of applications including staircase lighting and pump overrun for central heating.

The device has a blank face plate. Its primary advantage is that it can be mounted remotely away from the load it is controlling. The unit is particularly useful in areas where direct contact with electrical switches is prohibited.

Due to our policy of continuous improvement, we reserve the right to change specifications without notice.
All information was correct at time of when this product file was produced - June 2020

Prefect Controls Limited, Unit 2, Church Field Business Park, Church Field Road, Sudbury CO10 2YF
01787 320604 | mail@prefectcontrols.com | prefectcontrols.com

10081