

# PRE9230

## Run-back timer



Cleverly simple  
control of energy.



### Key features

- User-adjustable push-button timer with 15-minute increments up to 2 hours
- On/off button
- 230V AC at 50Hz
- Up to 16Amp output, (suitable for loads up to 3kW)
- Live, Neutral, Live output Load: 16A resistive, 10A incandescent, 6A fluorescent, 3A low energy lighting
- 4mm<sup>2</sup> terminal capacity
- 5-year warranty

**This versatile electronic timer is well suited for a variety of uses, from immersion heaters to lighting and heating/ventilation equipment.**

Run-back times can be selected in 15-minute intervals, whilst the easy to read display shows time remaining. An on/off button allows the user to cancel the program at any time.

Due to our policy of continuous improvement, we reserve the right to change specifications without notice. All information was correct at time of when this product file was produced - June 2020

**Prefect Controls Limited**, Unit 2, Church Field Business Park, Church Field Road, Sudbury CO10 2YF  
01787 320604 | mail@prefectcontrols.com | prefectcontrols.com

10082