

PRE9275

Hob run-back timer



Cleverly simple
control of energy.



Key features

- Available in 15 min Pre-set or 30 min pre-set
- Separate On Re-set button
- 230V AC at 50Hz
- Up to 25Amp capacity (suitable for resistive loads up to 5.5kW)
- Live, Neutral, switched live output connections
- 25A resistive, 6A fluorescent,
- 3A compact fluorescent,
- 3A low energy lighting
- 4mm² terminal capacity

This Simple to use electronic hob timer is ideally suited for use in student halls of residence. Its' robust design and large switching capacity makes it the sensible choice to avoid any risk of accidental fire.

Run-back times can be factory set for either 15 or 30 Minutes at point of ordering, set in the factory and delivered to site, thus removing any concerns of tampering. The display shows that the timer is active, whilst the re-set button allows the user to cancel the program at any time.

Please Note: This Prefect product is designed to limit the time the hob is powered on. It does not detect fire or alert if a pan fire occurs, therefore this product does not comply with EN 50615

Due to our policy of continuous improvement, we reserve the right to change specifications without notice. All information was correct at time of when this product file was produced - January 2020

Prefect Controls Limited, Unit 2, Church Field Business Park, Church Field Road, Sudbury CO10 2YF
01787 320604 | mail@prefectcontrols.com | prefectcontrols.com

10085